

The startpack truck mobile will provide an instant boost to all vehicles fitted with a 12V or 24V battery. With its two wheels and retractable handle it is designed as the ideal tool for site use. The 2 internal batteries (22 Ah) can also be used as a power source for 12 V DC appliances.

BOOSTER WITH INCREASED MOBILITY



✓ The STARTPACK TRUCK mobile is equipped with two wheels and a retractable handle for increased mobility.

BOOSTER PACK



✓ The STARTpack TRUCK mobile will provide an instant boost to all vehicles fitted with a 12V or 24V battery: cars, mobile homes, vans and smaller trucks (< 19t)

| START | | | |
|---------|-------|--------|--------|
| Battery | 1V/C | CC | PEAK |
| 12 V | 750 A | 1450 A | 3200 A |
| 24 V | 650 A | 1300 A | 1600 A |

INTEGRATED VOLTMETER



✓ The Startpack Truck mobile contains a built-in battery tester to display the charge status of the internal batteries.

POWER SUPPLY



✓ Designed to be use when there is no mains supply around, STARTpack TRUCK has 2 internal batteries of 22 Ah each. It can be also be used as a source of power to supply 12V to electrical appliances such as a TV, lights, a laptop etc.








Supplied with a 12V charger (ref. 054684) (UK : ref. 054691)

PROFESSIONAL EQUIPMENT

- ✓ **Automatic charger 230V /12 V Floating** : automatic charge of the internal batteries that can be used safely without supervision.
 - Designed to recharge batteries up to 100% for increased life cycle and performance.
 - Safe to be left connected to the mains permanently (charge is recommended after each use).
- ✓ **ON/OFF battery breaker** : protection against overvoltage when clamps are connected on the battery.
- ✓ **Sound alarm** to alert the user in case of polarity reversal.
- ✓ **Visual reminder** to remind the user of charging the internal batteries.
- ✓ **Copper cables 2 x 1.80 m, ø25 mm² with 600 A insulated clamps 600 A.**
- ✓ **Equipped with a 300 A front fuse** (supplied with a replacement fuse).



| INSIDE | START  | | | | TEST  | EXTERNAL 12V DC / 2A DC  | PROTECTION  | | POWER SUPPLY  | 300 A | 38 x 23,5 x 58,5 cm | 21 kg |
|-----------|---|--------|-------------|--------------|--|---|---|-------------|--|-------|---------------------|-------|
| | Battery | I 1V/C | Cranking CC | Peak Battery | | | ON/OFF | Sound Alarm | 12V DC | | | |
| 2 x 22 Ah | 12 V | 750 A | 1450 A | 3200 A | - | EXTERNAL 12V DC / 2A DC | • | • | 12V DC | 300 A | 38 x 23,5 x 58,5 | 21 |
| | 24 V | 650 A | 1300 A | 1600 A | | | | | | | | |